

TECHNICAL LIBRARY

MODEL: FT-2000

File No.	TL_FT-2000.doc	Serial Number range	ALL
Date of issue :	06/09/21	Page	1

Type	Frequency Band										Jumper			
	1.8MHz	3.5MHz	5MHz	7MHz	10MHz	14MHz	18MHz	21MHz	24MHz	28MHz	50MHz	JP3000	JP3001	JP3002
EU	1.815000- 1.889999	3.500000- 3.799999	/	7.000000- 7.099999	10.100000- 10.149999	14.000000- 14.349999	18.068000- 18.167999	21.000000- 21.449999	24.890000- 24.989999	28.000000- 29.699999	50.080000- 50.399999	○	○	-
FRA	1.810000- 1.849999	↑	/	↑	↑	↑	↑	↑	↑	↑	50.200000- 51.199999	-	-	○
UK	1.810000 1.999999	↑	5.266000, 5.280000, 5.290000, 5.400000, 5.405000	7.000000- 7.199999	↑	↑	↑	↑	↑	↑	50.000000- 51.999999	-	○	-
EXP/ AUS	1.800000- 1.999999	3.500000- 3.999999	/	7.000000- 7.299999	↑	↑	↑	↑	↑	↑	50.000000- 53.999999	-	○	○
USA	↑	↑	5.167500, 5.332000, 5.348000, 5.368000, 5.373000, 5.405000	↑	↑	↑	↑	↑	↑	↑	↑	-	-	-
JPN	1.810000- 1.824999, 1.907500- 1.912499	3.500000- 3.574999, 3.747000- 3.753999, 3.791000- 3.804999	4.630000	7.000000- 7.099999	↑	↑	↑	↑	↑	↑	↑	○	-	-




Figure 1




Figure 2





Figure 3



Then full reset, power on while pushing 'Fast' key and 'Lock' key at the same time.